



CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Advanced Micro Devices
TYAN Tomcat K8E (S2865), AMD Opteron(TM) 185

SPECint_rate2000 = **41.1**
SPECint_rate_base2000 = **36.6**

SPEC license #: 49 | Tested by: AMD Austin, Texas | Test date: Feb-2006 | Hardware Avail: Mar-2006 | Software Avail: Nov-2005

Benchmark	Base Copies	Base Runtime	Base Ratio	Copies	Runtime	Ratio
164.gzip	2	88.8	36.6	2	88.5	36.7
175.vpr	2	112	28.9	2	107	30.2
176.gcc	2	61.5	41.5	2	62.3	41.0
181.mcf	2	306	13.6	2	189	22.0
186.crafty	2	43.1	53.8	2	41.9	55.3
197.parser	2	152	27.4	2	118	35.2
252.eon	2	48.2	62.6	2	41.6	72.5
253.perlbnk	2	102	40.8	2	89.3	46.8
254.gap	2	68.7	37.2	2	68.7	37.2
255.vortex	2	71.0	62.0	2	66.1	66.7
256.bzip2	2	103	33.8	2	103	33.8
300.twolf	2	210	33.2	2	165	42.3

Hardware

CPU: AMD Opteron(TM) 185 (939-pin)
 CPU MHz: 2600
 FPU: Integrated
 CPU(s) enabled: 2 cores, 1 chip, 2 cores/chip
 CPU(s) orderable: 1
 Parallel: No
 Primary Cache: 64KBI + 64KBD (on chip) per core
 Secondary Cache: 1024KB (I+D) (on chip) per core
 L3 Cache: N/A
 Other Cache: N/A
 Memory: 2x512MB, DDR400 CL2
 Disk Subsystem: SATA, 250 GB
 Other Hardware: None

Software

Operating System: SuSE Linux Enterprise Server 9 SP3 (64-bit)
 Compiler: PathScale EKOPath(TM) Compiler Suite, Release 2.3
 File System: Linux/ext3
 System State: Multi-user, run level 3

Notes/Tuning Information

+FDO: PASS1= -fb_create fbdata PASS2= -fb_opt fbdata

Baseline optimization flags:

C programs: -Ofast +FDO
 C++ programs: -Ofast +FDO

Portability Flags:

186.crafty: -DLINUX_i386
 252.eon: -DHAS_ERRLIST -DSPEC_CPU2000_LP64
 253.perlbnk: -DSPEC_CPU2000_LINUX_I386 -DSPEC_CPU2000_NEED_BOOL
 -DSPEC_CPU2000_GLIBC22 -DSPEC_CPU2000_LP64
 254.gap: -DSYS_IS_USG -DSYS_HAS_IOCTL_PROTO -DSYS_HAS_TIME_PROTO
 -DSYS_HAS_CALLOC_PROTO -DSPEC_CPU2000_LP64
 255.vortex: -DSPEC_CPU2000_LP64

Peak Tuning:

164.gzip: -O3 -ipa -WOPT:val=0 -OPT:unroll_size=0 +FDO
 175.vpr: -O3 -ipa -m32 +FDO
 176.gcc: -O3 -IPA:plimit=10000 -LNO:opt=0 -OPT:goto=off +FDO



CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Advanced Micro Devices
TYAN Tomcat K8E (S2865), AMD Opteron(TM) 185

SPECint_rate2000 = 41.1
SPECint_rate_base2000 = 36.6

SPEC license #: 49 | Tested by: AMD Austin, Texas | Test date: Feb-2006 | Hardware Avail: Mar-2006 | Software Avail: Nov-2005

Notes/Tuning Information (Continued)

```
181.mcf:      -O3 -ipa -IPA:field_reorder=on -m32 +FDO
186.crafty:   -Ofast -CG:local_fwd_sched=on -LNO:opt=0 -WOPT:val=0 +FDO
197.parser:   -O3 -ipa -m32 -IPA:ctype=on +FDO
252.eon:      -Ofast -CG:gcm=off:p2align_freq=1:prefetch=off -IPA:plimit=4000
              -OPT:treeheight=on -TENV:X=4:frame_pointer=off -fno-exceptions
              -LNO:fu=10:full_unroll_outer=on -GRA:optimize_boundary=on +FDO
253.perlbnk:  -O2 -ipa -OPT:Ofast:transform_to_memlib=off
              -fno-math-errno -IPA:plimit=10000 +FDO
255.vortex:   -Ofast -OPT:goto=off -CG:p2align=on
              -GRA:optimize_boundary=on -IPA:min_hotness=120 +FDO
256.bzip2:    basepeak = true
300.twolf:    -O2 -CG:gcm=off:p2align_freq=100000
              -OPT:Ofast:unroll_times_max=8:unroll_size=256:alias=disjoint
              -WOPT:mem_opnds=on -m32 +FDO
```

Corsair CMX512-3200XL memory used in Dual Channel configuration.

Memory timings manually set in BIOS: Command Rate=1T

BIOS rev 3.00

The tested system can be assembled using a standard ATX case and an Antec True 550 watt EPS12V Power Supply.