



CFP2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Fujitsu Limited
PRIMEPOWER900 (2160MHz)

SPECfp2000 = 2139

SPECfp_base2000 = 1808

SPEC license #: 19 Tested by: Fujitsu Limited Test date: Apr-2005 Hardware Avail: Jun-2005 Software Avail: Apr-2004

Benchmark	Reference Time	Base Runtime	Base Ratio	Runtime	Ratio
168.wupwise	1600	103	1556	93.2	1717
171.swim	3100	250	1240	84.1	3685
172.mgrid	1800	171	1052	150	1198
173.applu	2100	128	1646	107	1956
177.mesa	1400	114	1232	92.9	1506
178.galgel	2900	61.1	4746	50.7	5717
179.art	2600	10.8	24117	10.8	24119
183.earth	1300	59.9	2172	58.1	2239
187.facerec	1900	65.2	2915	63.1	3013
188.amp	2200	157	1404	140	1566
189.lucas	2000	171	1167	165	1211
191.fma3d	2100	209	1006	196	1070
200.sixtrack	1100	189	582	154	712
301.apsi	2600	186	1399	186	1399

Hardware

CPU: SPARC64 V
CPU MHz: 2160
FPU: Integrated
CPU(s) enabled: 1 core, 1 chip, 1 core/chip
CPU(s) orderable: 1 to 16 (increments of 1)
Parallel: None
Primary Cache: 128KBI + 128KBD on chip
Secondary Cache: 4MB(I+D) on chip
L3 Cache: None
Other Cache: None
Memory: 8192MB
Disk Subsystem: 1 x 36.4GB SCSI (10000rpm)
Other Hardware: None

Software

Operating System: Solaris 9 4/04
Compiler: (Fortran) Fujitsu Parallelnavi 2.3 with patch 913221-03
Sun Studio 9
Sun Performance Library 9
(C)
Sun Studio 9
File System: ufs
System State: multi user

Notes/Tuning Information

```
FDO: (for Parallelnavi 2.3)
fdo_pre0=rm -rf `pwd`/*.f.d
PASS1=-Kpg
PASS2=-Kpu
FDO: (for Sun Studio 9)
fdo_pre0=rm -rf ./feedback.profile ./SunWS_cache
PASS1=-xprofile=collect:./feedback
PASS2=-xprofile=use:./feedback
```

```
Floating point base flags:
(using Fortran compiler of Sun Studio 9)
-fast -xtarget=ultra3cu -xipo=2 ONESTEP=yes FDO
(using C compiler of Sun Studio 9)
-fast -xtarget=ultra3 -xipo=2 ONESTEP=yes FDO
```

Floating point peak flags:



CFP2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Fujitsu Limited
PRIMEPOWER900 (2160MHz)

SPECfp2000 = 2139
SPECfp_base2000 = 1808

SPEC license #: 19 | Tested by: Fujitsu Limited | Test date: Apr-2005 | Hardware Avail: Jun-2005 | Software Avail: Apr-2004

Notes/Tuning Information (Continued)

(using Fortran compiler of Parallelnavi 2.3)

168.wupwise: -Kfast_GP2=3,prefetch_infer,alignl=64,unroll=4,
prefetch_cache_level=3 -O5 -x dir=./ FDO
172.mgrid: -Kfast_GP2=2,GREG_SYSTEM -O4 -Kcommonpad=180,alignc=64
189.lucas: -Kfast_GP2=3 -O5 -x dir=./ -Kunroll=2 FDO
191.fma3d: -Am -Kfast_GP2=3,GREG_SYSTEM -O4 -x dir=./ -x70 -Kprefetch_infer FDO
200.sixtrack: -Kfast_GP2=3 -O4 -x dir=./ -Kunroll=3 -fs FDO

(using Fortran compiler of Sun Studio 9)

171.swim: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:4096/64/4
-xpad=common:1700 -Qoption iropt -Ainline:cs=700,Atile:skewp:b10
173.applu: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:4096/64/4
-xipo=2 -Qoption cg -Qlp=1-av=192-t=4-fa=1-fl=0
-Qoption iropt -Aujam:inner=g ONESTEP=yes FDO
178.galgel: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:4096/64/4
-xipo=2 -Qoption iropt -Addint:sf=9 -xlic_lib=sunperf
RM_SOURCES=lapak.f90 ONESTEP=yes FDO
187.facerec: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:4096/64/4
-xprefetch=latx:1.6 ONESTEP=yes FDO
301.apsi: basepeak=yes

(using C compiler of Sun Studio 9)

177.mesa: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:4096/64/4
-xchip=ultra2 -xalias_level=strong -xipo=2 -xrestrict
ONESTEP=yes FDO
179.art: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:4096/64/4
-xipo=2 ONESTEP=yes FDO
183.earthquake: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:4096/64/4
-xalias_level=strong -W2,-whole -Wc,-Qms_pipe-pref,
-Qlp=1-av=512-t=6-fa=1-fl=1 ONESTEP=yes FDO
188.ammp: -fast -xalias_level=std -xipo=2 ONESTEP=yes FDO

Portability:

178.galgel: -e -fixed

System Tunables:

(for /etc/system)

```
set consistent_coloring=1
set tune_t_fsflushr=86400
set autoup=86400
```

Shell Environments:

```
Stack size set to unlimited via "ulimit -s unlimited"
MPSSHEAP=4M
MPSSSTACK=4M
LD_PRELOAD=mpss.so.1
```

System board used with only ONE CPU present.

Small configuration memory system mode used ("4cpu mode", enabled via system console).

Sun Studio 9, posted at URL <http://www.sun.com/software/products/studio/previous/9/index.xml>
was used for this submission.