



# CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Sun Microsystems  
Sun Fire X4200

SPECint2000 = 1940  
SPECint\_base2000 = 1761

SPEC license #: 6 Tested by: Sun Microsystems, Santa Clara Test date: Mar-2006 Hardware Avail: May-2006 Software Avail: Jan-2006

Benchmark	Reference Time	Base Runtime	Base Ratio	Runtime	Ratio	1000 2000 3000 4000			
164.gzip	1400	89.4	1566	87.2	1605	[Bar chart showing runtime and ratio for 164.gzip]			
175.vpr	1400	97.0	1443	89.6	1563	[Bar chart showing runtime and ratio for 175.vpr]			
176.gcc	1100	53.9	2042	53.3	2066	[Bar chart showing runtime and ratio for 176.gcc]			
181.mcf	1800	162	1108	151	1194	[Bar chart showing runtime and ratio for 181.mcf]			
186.crafty	1000	55.5	1801	38.4	2601	[Bar chart showing runtime and ratio for 186.crafty]			
197.parser	1800	118	1520	117	1533	[Bar chart showing runtime and ratio for 197.parser]			
252.eon	1300	44.8	2904	40.3	3226	[Bar chart showing runtime and ratio for 252.eon]			
253.perlbnk	1800	92.4	1948	86.5	2082	[Bar chart showing runtime and ratio for 253.perlbnk]			
254.gap	1100	70.4	1562	64.7	1699	[Bar chart showing runtime and ratio for 254.gap]			
255.vortex	1900	73.2	2594	58.0	3274	[Bar chart showing runtime and ratio for 255.vortex]			
256.bzip2	1500	105	1422	98.7	1520	[Bar chart showing runtime and ratio for 256.bzip2]			
300.twolf	3000	154	1942	148	2025	[Bar chart showing runtime and ratio for 300.twolf]			

### Hardware

CPU: AMD Opteron (TM) 256  
 CPU MHz: 3000  
 FPU: Integrated  
 CPU(s) enabled: 1 core, 1 chip, 1 core/chip  
 CPU(s) orderable: 1,2 (order by # of chips)  
 Parallel: No  
 Primary Cache: 64KBI + 64KBD (on chip) per core  
 Secondary Cache: 1024KB (I+D) (on chip) per core  
 L3 Cache: N/A  
 Other Cache: N/A  
 Memory: 8GB (4x2GB, PC3200 CL3 DDR ECC Registered SDRAM)  
 Disk Subsystem: SAS,36GB,10K RPM  
 Other Hardware: None

### Software

Operating System: Solaris 10 1/06  
 Compiler: Sun Studio 11  
 File System: ufs  
 System State: Multi-user

## Notes/Tuning Information

Compiler invocation:

C: cc  
CXX: CC

FDO: PASS1= -xprofile=collect:./feedback PASS2= -xprofile=use:./feedback  
fdo\_pre0: rm -rf ./feedback.profile

Integer base flags:

Base tuning for C programs : -fast -xcrossfile -xalias\_level=std +FDO ONESTEP=yes  
Base tuning for C++ programs: -fast -xcrossfile -xarch=amd64 +FDO ONESTEP=yes

Integer peak flags:

ONESTEP=yes +FDO for all benchmarks

164.gzip: -fast -xpagesize=2m -xcrossfile -M /usr/lib/ld/map.bssalign  
 175.vpr: -fast -xpagesize=2m -W2,-Ainline:inc=200:cs=500 -M /usr/lib/ld/map.bssalign -lmopt -lm  
 176.gcc: -fast -xipo=2 -Wd,-iropt-prof -xalias\_level=strong -xrestrict  
 181.mcf: -fast -xpagesize=2m -xcrossfile -M /usr/lib/ld/map.bssalign  
 186.crafty: -fast -xrestrict -xipo=2 -xprefetch -xarch=amd64 -xpagesize=2m  
 -M /usr/lib/ld/map.bssalign -Wd,-iropt-prof -W2,-Ashort\_ldst:ldld



# CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Sun Microsystems  
Sun Fire X4200

SPECint2000 =	1940
SPECint_base2000 =	1761

SPEC license #:	6	Tested by:	Sun Microsystems, Santa Clara	Test date:	Mar-2006	Hardware Avail:	May-2006	Software Avail:	Jan-2006
-----------------	---	------------	-------------------------------	------------	----------	-----------------	----------	-----------------	----------

## Notes/Tuning Information (Continued)

```

-W2,-Ainline:rs=50
197.parser: -fast -xpagesize=2m -xipo=2 -W2,-Ainline:inc=200:cs=500 -M /usr/lib/ld/map.bssalign
252.eon: -fast -xipo=2 -qoption CC -iropt-prof -xvector -qoption iropt -Abcopy -xalias_level
        -xarch=amd64 -xrestrict -Qoption ube -xcallee=yes -xregs=frameptr
253.perlbnk: -fast -xcrossfile -M /usr/lib/ld/map.bssalign -lbsdmalloc
254.gap: -fast -xipo=2 -Wd,-iropt-prof -xvector -W2,-Abcopy -lbsdmalloc -xprefetch
        -W2,-Ainline:cp=5:rs=1300:irs=3300:inc=100 -W2,-Arestrict_g
255.vortex: -fast -xipo=2 -Wd,-iropt-prof -lbsdmalloc -xrestrict -xprefetch -M /usr/lib/ld/map.bssalign
256.bzip2: -fast -xpagesize=2m -xcrossfile -xarch=sse2 -Xc -M /usr/lib/ld/map.bssalign -lbsdmalloc
300.twolf: -fast -xipo=2 -Wd,-iropt-prof -xrestrict -M /usr/lib/ld/map.bssalign

```

### Portability:

```

186.crafty (base): -DSOLARIS_X86
186.crafty (peak): -DSOLARIS_X64
252.eon: -DSPEC_CPU2000_LP64 -DUSE_STRERROR
253.perlbnk: -DSPEC_CPU2000_SOLARIS_X86
254.gap: -DSYS_IS_USG -DSYS_HAS_SIGNAL_PROTO -DSYS_HAS_TIME_PROTO -DSYS_HAS_CALLOC_PROTO

```

### Shell Environments:

Stack size set to unlimited via "ulimit -s unlimited"

System was tested in 1 chips configuration

Default BIOS setting was used

This result was measured on the Sun Fire X4200. In addition, Sun has submitted the same result for the Sun Fire X4100, which is electronically equivalent to the Sun Fire X4200.